



**Classic Par 18**

**User Manual**

---

## I Checking

Welcome to use our products, we are glad to offer you our highest quality and best service. Please check if the following parts are inside the package after you open the package:

User manual 1 piece      Light equipment 1 piece  
3 chips signal wire 1 piece

## II Skill parameter

1. Voltage: AC90V-240V 50/60Hz
2. Power: 200W
3. LED: 10W/12W/15W (4in1/5in1/6in1)
4. LED QTY: 18PCS
5. Control channel: 8CH
6. RGBW/RGBWA/RGBWA-UV colors infinite mixing  
possibility+strobe+dimmer+multi function

## III Function instruction



## IV LED Display function

Serial NO.	Display	Function instruction
1	D001	8 DMX channel add code, (001-512) UP, DOWN button add and subtract add code value
2	CC00	Colorful transition, (01—99) UP, DOWN button change the speed of transition
3	CP00	Colorful Pulse change, Gradual change, (01—99) UP, DOWN button change the Pulse change, Gradual change speed
4	DE00	Colorful combine change, (01—99) UP, DOWN button change combine speed
5	BE00	Seven colors with sound

6	R001	Red color selection (000—255) UP, DOWN button change color
7	G001	Green color selection (000—255) UP, DOWN button change color
8	B001	Blue color selection (000—255) UP, DOWN button change color
9	O001	White color selection (000—255) UP, DOWN button change color

## V DMX512 Channel function

Channel	Channel Function	Directions
CH1	Dimmer All	R/G/B/W, linear dimmer brightness from dark to bright
CH2	Strobe All	R/G/B/W, strobe, speed from slow to fast
CH3	Function Selection	0-50, DMX 8 channel control, 51-100 saltus step, 101-150 gradual change, 151-200 pulse, 201-255: sound active
CH4	Function Speed	Function speed from slow to fast
CH5	Red Dimmer	Red dimmer, linear dimmer, from dark to bright
CH6	Green Dimmer	Green dimmer, linear dimmer, from dark to bright
CH7	Blue Dimmer	Blue dimmer, linear dimmer, from dark to bright
CH8	White Dimmer	White dimmer, linear dimmer, from dark to bright

## VI Announce

1. This product before leaving the factory, the operation and package of this unit were checked and passed quality inspection. Users must read and observe the directions described in this user manual. Any damage caused through misuse or not following the user manual during the warrantee period will not be covered by the manufacturer's guarantee.
2. We reserve the high to modify the inform action stated in this user manual at any time and without prior-notice.